


PRODUCT FEATURES

- High level of integration
- 600V IGBT³ CHIP(Trench+Field Stop technology)
- Low saturation voltage and positive temperature coefficient
- Fast switching and short tail current
- Free wheeling diodes with fast and soft reverse recovery
- Industry standard package with insulated copper base plate and soldering pins for PCB mounting
- Temperature sense included

APPLICATIONS

- AC motor control
- Motion/servo control
- Inverter and power supplies



Rectifier+Brake+Inverter

IGBT-inverter

ABSOLUTE MAXIMUM RATINGS($T_C=25^{\circ}\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions	Values	Unit
V_{CES}	Collector Emitter Voltage	$T_J=25^{\circ}\text{C}$	V
V_{GES}	Gate Emitter Voltage		
I_C	DC Collector Current	$T_C=25^{\circ}\text{C}, T_{Jmax}=175^{\circ}\text{C}$	60
		$T_C=80^{\circ}\text{C}, T_{Jmax}=175^{\circ}\text{C}$	50
I_{CM}	Repetitive Peak Collector Current	$t_p=1\text{ms}$	100
P_{tot}	Power Dissipation Per IGBT	$T_C=25^{\circ}\text{C}, T_{Jmax}=175^{\circ}\text{C}$	190

Diode-inverter

ABSOLUTE MAXIMUM RATINGS ($T_C=25^{\circ}\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions	Values	Unit
V_{RRM}	Repetitive Reverse Voltage	$T_J=25^{\circ}\text{C}$	V
$I_{F(AV)}$	Average Forward Current		A
I_{FRM}	Repetitive Peak Forward Current	$t_p=1\text{ms}$	
I^2t		$T_J=125^{\circ}\text{C}, t=10\text{ms}, V_R=0\text{V}$	A ² S

MacMic Science & Technology Co., Ltd.

Add: #18, Hua Shan Zhong Lu, New District, Changzhou City, Jiangsu Province, P. R. of China

Tel.: +86-519-85163708 Fax: +86-519-85162291 Post Code: 213022 Website: www.macmicst.com

MMG50W060XB6EN

IGBT-inverter

ELECTRICAL CHARACTERISTICS ($T_C=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions		Min.	Typ.	Max.	Unit
$V_{GE(th)}$	Gate Emitter Threshold Voltage	$V_{CE}=V_{GE}, I_C=0.8\text{mA}$	4.9	5.8	6.5	V
$V_{CE(sat)}$	Collector Emitter Saturation Voltage	$I_C=50\text{A}, V_{GE}=15\text{V}, T_J=25^\circ\text{C}$		1.45	1.9	
		$I_C=50\text{A}, V_{GE}=15\text{V}, T_J=125^\circ\text{C}$		1.6		
		$I_C=50\text{A}, V_{GE}=15\text{V}, T_J=150^\circ\text{C}$		1.7		
I_{CES}	Collector Leakage Current	$V_{CE}=600\text{V}, V_{GE}=0\text{V}, T_J=25^\circ\text{C}$			1	mA
		$V_{CE}=600\text{V}, V_{GE}=0\text{V}, T_J=150^\circ\text{C}$			10	mA
I_{GES}	Gate Leakage Current	$V_{CE}=0\text{V}, V_{GE}=\pm 15\text{V}, T_J=25^\circ\text{C}$	-200		200	nA
R_{gint}	Integrated Gate Resistor			0		Ω
Q_g	Gate Charge	$V_{CE}=300\text{V}, I_C=50\text{A}, V_{GE}=\pm 15\text{V}$		500		nC
C_{ies}	Input Capacitance	$V_{CE}=25\text{V}, V_{GE}=0\text{V}, f=1\text{MHz}$		3.1		nF
C_{res}	Reverse Transfer Capacitance				95	
$t_{d(on)}$	Turn on Delay Time	$V_{CC}=300\text{V}, I_C=50\text{A}$ $R_G=43\Omega,$	$T_J=25^\circ\text{C}$		100	ns
			$T_J=150^\circ\text{C}$		100	ns
t_r	Rise Time	$V_{GE}=\pm 15\text{V},$ Inductive Load	$T_J=25^\circ\text{C}$		60	ns
			$T_J=150^\circ\text{C}$		70	ns
$t_{d(off)}$	Turn off Delay Time	$V_{CC}=300\text{V}, I_C=50\text{A}$ $R_G=43\Omega,$	$T_J=25^\circ\text{C}$		600	ns
			$T_J=150^\circ\text{C}$		700	ns
t_f	Fall Time	$V_{GE}=\pm 15\text{V},$ Inductive Load	$T_J=25^\circ\text{C}$		40	ns
			$T_J=150^\circ\text{C}$		60	ns
E_{on}	Turn on Energy	$V_{CC}=300\text{V}, I_C=50\text{A}$ $R_G=43\Omega,$	$T_J=25^\circ\text{C}$		2.3	mJ
			$T_J=125^\circ\text{C}$		2.75	mJ
			$T_J=150^\circ\text{C}$		2.9	mJ
E_{off}	Turn off Energy	$V_{GE}=\pm 15\text{V},$ Inductive Load	$T_J=25^\circ\text{C}$		1.75	mJ
			$T_J=125^\circ\text{C}$		2.1	mJ
			$T_J=150^\circ\text{C}$		2.15	mJ
I_{SC}	Short Circuit Current	$t_{psc}\leq 6\mu\text{s}, V_{GE}=15\text{V}$ $T_J=150^\circ\text{C}, V_{CC}=360\text{V}$		250		A
R_{thJC}	Junction to Case Thermal Resistance (Per IGBT)				0.8	K/W

Diode-inverter

ELECTRICAL CHARACTERISTICS ($T_C=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions		Min.	Typ.	Max.	Unit
V_F	Forward Voltage	$I_F=50\text{A}, V_{GE}=0\text{V}, T_J=25^\circ\text{C}$		1.55	1.95	V
		$I_F=50\text{A}, V_{GE}=0\text{V}, T_J=125^\circ\text{C}$		1.50		
		$I_F=50\text{A}, V_{GE}=0\text{V}, T_J=150^\circ\text{C}$		1.45		
I_{RRM}	Max. Reverse Recovery Current	$I_F=50\text{A}, V_R=300\text{V}$		36		A
Q_{RR}	Reverse Recovery Charge	$dI_F/dt=-900\text{A}/\mu\text{s}$		3.55		μC
E_{rec}	Reverse Recovery Energy	$T_J=150^\circ\text{C}$		0.6		mJ
R_{thJCD}	Junction to Case Thermal Resistance (Per Diode)				1.2	K/W

MMG50W060XB6EN

Diode-RECTIFIER

ABSOLUTE MAXIMUM RATINGS ($T_C=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions		Values	Unit
V_{RRM}	Repetitive Reverse Voltage	$T_J=25^\circ\text{C}$	1600	V
$I_{F(AV)}$	Average Forward Current Per Diode	$T_C=80^\circ\text{C}$	55	A
I_{FRMS}	R.M.S. Forward Current Per Diode		85	
I_{RMS}	R.M.S. Current at rectifier output		125	
I_{FSM}	Non Repetitive Surge Forward Current	$T_J=45^\circ\text{C}$, $t=10\text{ms}$, 50Hz	645	A
		$T_J=45^\circ\text{C}$, $t=8.3\text{ms}$, 60Hz	710	
I^2t		$T_J=45^\circ\text{C}$, $t=10\text{ms}$, 50Hz	2080	A ² S
		$T_J=45^\circ\text{C}$, $t=8.3\text{ms}$, 60Hz	2090	

Diode-RECTIFIER

ELECTRICAL CHARACTERISTICS ($T_C=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions		Min.	Typ.	Max.	Unit
V_F	Forward Voltage	$I_F=50\text{A}$, $T_J=25^\circ\text{C}$		1.05	1.2	V
		$I_F=50\text{A}$, $T_J=150^\circ\text{C}$		1.00		V
I_R	Reverse Leakage Current	$V_R=1600\text{V}$, $T_J=25^\circ\text{C}$			50	μA
		$V_R=1600\text{V}$, $T_J=150^\circ\text{C}$			1	mA
R_{thJCD}	Junction to Case Thermal Resistance (Per Diode)				0.62	K/W

IGBT-Brake chopper

ABSOLUTE MAXIMUM RATINGS ($T_C=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions		Values	Unit
V_{CES}	Collector Emitter Voltage	$T_J=25^\circ\text{C}$	600	V
V_{GES}	Gate Emitter Voltage		± 20	
I_C	DC Collector Current	$T_C=25^\circ\text{C}$, $T_{Jmax}=175^\circ\text{C}$	27	A
		$T_C=80^\circ\text{C}$, $T_{Jmax}=175^\circ\text{C}$	20	
I_{CM}	Repetitive Peak Collector Current	$t_p=1\text{ms}$	40	A
P_{tot}	Power Dissipation Per IGBT	$T_C=25^\circ\text{C}$, $T_{Jmax}=175^\circ\text{C}$	83	W

Diode-Brake chopper

ABSOLUTE MAXIMUM RATINGS ($T_C=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions		Values	Unit
V_{RRM}	Repetitive Reverse Voltage	$T_J=25^\circ\text{C}$	600	V
$I_{F(AV)}$	Average Forward Current		20	A
I_{FRM}	Repetitive Peak Forward Current	$t_p=1\text{ms}$	40	
I^2t		$T_J=125^\circ\text{C}$, $t=10\text{ms}$, $V_R=0\text{V}$	49	A ² S

MMG50W060XB6EN

IGBT-Brake chopper

ELECTRICAL CHARACTERISTICS ($T_C=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions		Min.	Typ.	Max.	Unit
$V_{GE(th)}$	Gate Emitter Threshold Voltage	$V_{CE}=V_{GE}, I_C=0.3\text{mA}$	4.9	5.8	6.5	V
$V_{CE(sat)}$	Collector Emitter Saturation Voltage	$I_C=20\text{A}, V_{GE}=15\text{V}, T_J=25^\circ\text{C}$		1.55	2	
		$I_C=20\text{A}, V_{GE}=15\text{V}, T_J=125^\circ\text{C}$		1.7		
		$I_C=20\text{A}, V_{GE}=15\text{V}, T_J=150^\circ\text{C}$		1.8		
I_{CES}	Collector Leakage Current	$V_{CE}=600\text{V}, V_{GE}=0\text{V}, T_J=25^\circ\text{C}$			1	mA
		$V_{CE}=600\text{V}, V_{GE}=0\text{V}, T_J=150^\circ\text{C}$			10	mA
I_{GES}	Gate Leakage Current	$V_{CE}=0\text{V}, V_{GE}=\pm 15\text{V}, T_J=25^\circ\text{C}$	-400		400	nA
R_{gint}	Integrated Gate Resistor					Ω
Q_g	Gate Charge	$V_{CE}=300\text{V}, I_C=20\text{A}, V_{GE}=\pm 15\text{V}$		200		nC
C_{ies}	Input Capacitance	$V_{CE}=25\text{V}, V_{GE}=0\text{V}, f=1\text{MHz}$		1.1		nF
C_{res}	Reverse Transfer Capacitance				32	
$t_{d(on)}$	Turn on Delay Time	$V_{CC}=300\text{V}, I_C=20\text{A}$ $R_G=18\Omega,$ $V_{GE}=\pm 15\text{V},$ Inductive Load	$T_J=25^\circ\text{C}$		20	ns
			$T_J=150^\circ\text{C}$		20	ns
t_r	Rise Time	$V_{GE}=\pm 15\text{V},$ Inductive Load	$T_J=25^\circ\text{C}$		13	ns
			$T_J=150^\circ\text{C}$		17	ns
$t_{d(off)}$	Turn off Delay Time	$V_{CC}=300\text{V}, I_C=20\text{A}$ $R_G=18\Omega,$ $V_{GE}=\pm 15\text{V},$ Inductive Load	$T_J=25^\circ\text{C}$		120	ns
			$T_J=150^\circ\text{C}$		150	ns
t_f	Fall Time	$V_{GE}=\pm 15\text{V},$ Inductive Load	$T_J=25^\circ\text{C}$		70	ns
			$T_J=150^\circ\text{C}$		100	ns
E_{on}	Turn on Energy	$V_{CC}=300\text{V}, I_C=20\text{A}$ $R_G=18\Omega,$ $V_{GE}=\pm 15\text{V},$ Inductive Load	$T_J=25^\circ\text{C}$		0.32	mJ
			$T_J=125^\circ\text{C}$		0.44	mJ
			$T_J=150^\circ\text{C}$		0.49	mJ
E_{off}	Turn off Energy	$V_{GE}=\pm 15\text{V},$ Inductive Load	$T_J=25^\circ\text{C}$		0.44	mJ
			$T_J=125^\circ\text{C}$		0.56	mJ
			$T_J=150^\circ\text{C}$		0.59	mJ
I_{SC}	Short Circuit Current	$t_{psc}\leq 6\mu\text{s}, V_{GE}=15\text{V}$ $T_J=150^\circ\text{C}, V_{CC}=360\text{V}$		100		A
R_{thJC}	Junction to Case Thermal Resistance (Per IGBT)				1.8	K/W

Diode-inverter

ELECTRICAL CHARACTERISTICS ($T_C=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions		Min.	Typ.	Max.	Unit
V_F	Forward Voltage	$I_F=20\text{A}, V_{GE}=0\text{V}, T_J=25^\circ\text{C}$		1.60	2.00	V
		$I_F=20\text{A}, V_{GE}=0\text{V}, T_J=125^\circ\text{C}$		1.55		
		$I_F=20\text{A}, V_{GE}=0\text{V}, T_J=150^\circ\text{C}$		1.50		
I_{RRM}	Max. Reverse Recovery Current	$I_F=20\text{A}, V_R=300\text{V}$		40		A
Q_{RR}	Reverse Recovery Charge	$dI_F/dt=-1800\text{A}/\mu\text{s}$		2.2		μC
E_{rec}	Reverse Recovery Energy	$T_J=150^\circ\text{C}$		0.47		mJ
R_{thJCD}	Junction to Case Thermal Resistance (Per Diode)				2.5	K/W

MMG50W060XB6EN

NTC CHARACTERISTICS ($T_C=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions	Min.	Typ.	Max.	Unit
R_{25}	Resistance $T_C=25^\circ\text{C}$		5		$\text{K}\Omega$
$B_{25/50}$	$R_2 = R_{25} \exp [B_{25/50}(1/T_2 - 1/(298.15 \text{ K}))]$		3375		K

MODULE CHARACTERISTICS ($T_C=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter/Test Conditions	Values	Unit
T_{Jmax}	Max. Junction Temperature	Inverter, Brake-Chopper	175
		Rectifier	150
T_{Jop}	Operating Temperature	-40~150	$^\circ\text{C}$
T_{stg}	Storage Temperature	-40~125	
V_{isol}	Isolation Breakdown Voltage	AC, 50Hz(R.M.S), t=1minute	3000
CTI	Comparative Tracking Index		>200
Md	Mounting Torque	Recommended (M5)	2.5~5
Weight			300
			g




Figure 1. Typical Output Characteristics IGBT-inverter




Figure 2. Typical Output Characteristics IGBT-inverter




Figure 3. Typical Transfer characteristics IGBT-inverter




Figure 4. Switching Energy vs Gate Resistor IGBT-inverter




Figure 5. Switching Energy vs Collector Current IGBT-inverter




Figure 6. Reverse Biased Safe Operating Area IGBT-inverter




Figure 7. Diode Forward Characteristics Diode -inverter




Figure 8. Switching Energy vs Gate Resistor Diode -inverter




Figure 9. Switching Energy vs Forward Current Diode-inverter




Figure 10. Transient Thermal Impedance of Diode and IGBT-inverter




Figure 11. Diode Forward Characteristics Diode-rectifier




Figure 12. Typical Output Characteristics IGBT-brake chopper




Figure 13. Diode Forward Characteristics Diode-brake chopper




Figure 14. NTC Characteristics

MMG50W060XB6EN




Figure 15. Collector Current vs Case temperature IGBT -inverter




Figure 16. Forward current vs Case temperature Diode -inverter





Figure 17. Circuit Diagram

MMG50W060XB6EN



Dimensions in (mm)

Figure 18. Package Outline